



---

# HIGH POWER AUTO POWER ADAPTER

---



For assistance call Lind Technical Support at (800) 659-5956 or (952) 927-6303.

# INSTALLATION INSTRUCTIONS

---

This model of Lind Power Adapter is intended to be permanently mounted. Therefore, only qualified service personnel familiar with the wiring, mounting and operation of electrical accessories in the vehicle should attempt to install the adapter. Proper installation will ensure safe, reliable operation of the Lind power adapter.

The adapter comes with an input cable with two conductors. The white or red (positive) lead of the input cable must be connected to the battery with a cable of sufficient gauge to prevent excessive voltage drop. Wire gauge needed for reliable operation is dependent on the length of the wire from the power adapter's white or red input cable to the battery and the length of wire from the power adapter's black input cable to the chassis. The connection to the chassis must be clean and free from oxide, paint, or any other nonconductive coating. Use the table below to determine the minimum wire gauge by adding the chassis wire and positive wire for the total cable length.

Total Cable Length (f )	5	10	15	20	25	30	35	40
Wire Gauge (AWG)	16	12	10	10	8	8	6	6

The black lead of the input cable should be fastened to the chassis with a reliable and clean electrical connection. The adapter's positive cable must have an UL-listed fuse and fuse block installed inline within 18 inches of the battery. A fuse rated at a minimum of 15 amps and a maximum of 20 amps is recommended.

Install the power adapter in a location that allows for air flow around the adapter. Covering the power adapter and restricting airflow may cause the adapter to overheat and shut down. Secure the adapter using tie wraps, large screw clamps, brackets, etc. Mounting brackets for the high power adapters can be purchased from Lind Electronics. The adapter is not intended to be installed in the engine compartment or any other place where it can be exposed to moisture or excessive heat.

## TECHNICAL INFORMATION

---

Power Input:	Noted on label
Power Output:	Noted on label
Input Fuse:	Auto Mini - Noted on label (Replace with same fuse as in adapter)
Indicators:	LED on adapter (Output power present)
Features:	Output Short Circuit Protected Output Current Limit Input and Output Noise Filter Internal Overtemperature Shutdown Low Input Voltage Shutdown High Input Voltage Shutdown Automatic Reset of Safety Shutdown



# LIMITED WARRANTY

---

Lind Electronics, Inc. (LIND) warrants the circuit assembly portion of products manufactured by it to be free of defects in material and workmanship for a period of 3 years from the date of purchase under normal use. During this warranty period, LIND will, at its option, repair or replace the product at no charge for parts or labor when the product is returned postage paid as a complete unit to LIND. Proof of purchase and a letter explaining the problem must accompany the returned unit.

This warranty does not apply if any part of the adapter, its cables or connection jacks have been altered, subjected to abuse, accident or misuse. This warranty excludes incidental or consequential damage resulting from the product or the use of the product. This warranty is in lieu of all other warranties expressed or implied and no person is authorized to assume for LIND any other liability in conjunction with the use of the product and you may have other rights which may vary from state to state and country to country.

LIND ELECTRONICS, INC. HEREBY EXPRESSLY DISCLAIMS ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Lind Electronics, Inc. will not be liable for any claims, awards, damages or other liability arising out of the use of LIND products for life support applications whether in the nature of direct, indirect, consequential, special or punitive damages.



**Lind Electronics, Inc.**

---

[www.lindelectronics.com](http://www.lindelectronics.com)

[info@lindelectronics.com](mailto:info@lindelectronics.com)

[techsupport@lindelectronics.com](mailto:techsupport@lindelectronics.com)

Phone: (800) 659-5956

Lind, Lind Electronics, and the Lind logo are trademarks of Lind Electronics, Inc. All other

